

RED
HAWK *Architect™ User's Guide*

Copyright 2009 by Concurrent Computer Corporation. All rights reserved. This publication or any part thereof is intended for use with Concurrent products by Concurrent personnel, customers, and end-users. It may not be reproduced in any form without the written permission of the publisher.

The information contained in this document is believed to be correct at the time of publication. It is subject to change without notice. Concurrent makes no warranties, expressed or implied, concerning the information contained in this document.

To report an error or comment on a specific portion of the manual, photocopy the page in question and mark the correction or comment on the copy. Mail the copy (and any additional comments) to Concurrent Computer Corporation, 2881 Gateway Drive, Pompano Beach, FL 33069. Mark the envelope **“Attention: Publications Department.”** This publication may not be reproduced for any other reason in any form without written permission of the publisher.

Concurrent Computer Corporation and its logo are registered trademarks of Concurrent Computer Corporation. All other Concurrent product names are trademarks of Concurrent while all other product names are trademarks or registered trademarks of their respective owners. Linux® is used pursuant to a sublicense from the Linux Mark Institute.

Printed in U. S. A.

Revision History:	Level:	Effective With:
November 2008	000	RedHawk Linux 5.1
January 2009	100	RedHawk Linux 5.2
February 2009	200	RedHawk Linux 5.2
July 2009	300	RedHawk Linux 5.2
October 2009	400	RedHawk Linux 5.2

Scope of Manual

This manual describes the RedHawk Architect™, an easy-to-use GUI interface for creating and maintaining a runtime and development environment for a single board computer (SBC).

Structure of Manual

This manual consists of:

- Chapter 1, which introduces you to RedHawk Architect and guides you through its use.
- An Index containing an alphabetical reference to key terms and concepts and the pages where they occur in the text.

Syntax Notation

The following notation is used throughout this manual:

<i>italic</i>	Books, reference cards, and items that the user must specify appear in <i>italic</i> type. Special terms may also appear in <i>italic</i> .
list bold	User input appears in list bold type and must be entered exactly as shown. Names of directories, files, commands, options and man page references also appear in list bold type.
list	Operating system and program output such as prompts, messages and listings of files and programs appears in list type.
[]	Brackets enclose command options and arguments that are optional. You do not type the brackets if you choose to specify these options or arguments.
hypertext links	When viewing this document online, clicking on chapter, section, figure, table and page number references will display the corresponding text. Clicking on Internet URLs provided in blue type will launch your web browser and display the web site. Clicking on publication names and numbers in red type will display the corresponding manual PDF, if accessible.

Related Publications

The following table lists Concurrent documentation for RedHawk Architect and the components that can be installed using RedHawk Architect. Depending upon the

document, they are available online on RedHawk Linux systems or from Concurrent's documentation web site at <http://redhawk.ccur.com/docs>.

RedHawk Architect	Pub. Number
<i>RedHawk Architect Release Notes</i>	0898600
<i>RedHawk Architect User's Guide</i>	0898601
RedHawk Linux	
<i>RedHawk Linux Release Notes</i>	0898003
<i>RedHawk Linux User's Guide</i>	0898004
<i>RedHawk Linux Cluster Manager User's Guide</i>	0898016
<i>RedHawk Linux FAQ</i>	N/A
NightStar Development Tools	
<i>NightView User's Guide</i>	0898395
<i>NightTrace User's Guide</i>	0898398
<i>NightProbe User's Guide</i>	0898465
<i>NightTune User's Guide</i>	0898515

Contents

Preface	iii
----------------------	-----

Chapter 1 Using RedHawk Architect

Introducing Architect	1-1
Creating a root File System for Embedded Target Boards	1-1
Running Architect	1-2
Creating a New Session	1-3
Selecting Software to Install in the Image	1-5
Selecting Red Hat Packages	1-5
Using the Embedded RedHawk Package Groups View	1-6
Using the Red Hat Package Groups View	1-6
Using the All Packages View	1-7
Using the Selected Packages View	1-8
Selecting RedHawk OS Options	1-9
Selecting NightStar RT Options	1-10
Configuring an Image (before building)	1-11
Building an Image	1-12
Configuring an Image	1-17
Configuring General Settings	1-17
Configuring a Console	1-18
Configuring Networking	1-19
Configuring File System Options	1-21
Customizing an Image	1-23
Kernel Manager	1-23
Configure Custom Kernel	1-24
Import Kernel Configuration	1-27
Export Kernel Configuration	1-27
Build Custom Kernel	1-27
Remove Custom Kernel	1-29
Additional RPMs	1-29
Installing Board Support Packages	1-30
File Manager	1-31
Chroot Shell	1-31
Image Cleanup	1-33
Flashing an Image	1-35
Using Cluster Manager to Deploy an Architect Image	1-38
Editing an Existing Session	1-39
Updating Software with NUU	1-39

Index	Index-1
--------------------	---------

Illustrations

Figure 1-1 Opening RedHawk Architect Dialog	1-2
Figure 1-2 RedHawk Architect Main Window	1-3
Figure 1-3 New Session Dialog	1-4

Figure 1-4	Selecting Red Hat Packages, Embedded RedHawk Package Groups View	1-6
Figure 1-5	Selecting Red Hat Packages, Red Hat Package Groups View	1-7
Figure 1-6	Selecting Red Hat Packages, All Packages View	1-8
Figure 1-7	Selecting Red Hat Packages, Selected Packages View	1-9
Figure 1-8	Selecting RedHawk Options	1-10
Figure 1-9	Selecting NightStar Tools	1-11
Figure 1-10	Build Image Page	1-12
Figure 1-11	Build Prompt to Insert RHEL Media	1-13
Figure 1-12	Status of RHEL Installation	1-14
Figure 1-13	Build Prompt to Insert RedHawk Media	1-15
Figure 1-14	Status of RedHawk Installation	1-15
Figure 1-15	Build Prompt to Insert NightStar Media	1-16
Figure 1-16	Status of NightStar Installation	1-16
Figure 1-17	Build Completed Successfully Message	1-17
Figure 1-18	General Settings Configuration Page	1-18
Figure 1-19	Console Configuration Page	1-19
Figure 1-20	Network Configuration Page	1-20
Figure 1-21	Configure Network Device Dialog	1-21
Figure 1-22	File System Configuration Page	1-22
Figure 1-23	Kernel Manager Page	1-23
Figure 1-24	Custom Kernel Dialog	1-25
Figure 1-25	Linux Kernel Configuration Dialog	1-26
Figure 1-26	Initial Build Progress	1-27
Figure 1-27	Kernel Build Stages	1-28
Figure 1-28	Kernel Build Complete	1-29
Figure 1-29	Install Additional RPMs Page	1-30
Figure 1-30	File Manager Page	1-31
Figure 1-31	Chroot Shell Page	1-32
Figure 1-32	chroot Shell	1-33
Figure 1-33	Image Cleanup Page	1-34
Figure 1-34	Flash Image Page	1-35
Figure 1-35	Flash Image Dialog	1-36
Figure 1-36	Flash Destination Choice	1-36
Figure 1-37	Flash Copy Begins	1-37
Figure 1-38	Flash Dialog Error	1-37
Figure 1-39	Flash Copy Completed	1-38

Using RedHawk Architect

This chapter introduces you to the RedHawk Architect and provides instructions for its use.

Introducing Architect

RedHawk Architect is an easy-to-use GUI interface for configuring, building and flashing embedded solutions.

RedHawk Architect greatly simplifies the following tasks to create and maintain a runtime and development environment for single board computers (SBCs):

- installing custom configurations of the Red Hat® Enterprise Linux® distribution
- installing and configuring the RedHawk™ operating system
- installing SBC-specific board support packages (BSPs)
- installing NightStar™ application development tools
- maintaining and reconfiguring an SBC's root file system
- flashing the final root file system onto a compact flash device

With Architect, you choose the Linux and application modules that will be installed with the RedHawk kernel. For example, select networking, web server, web browser, database, X server, minimal or all packages. Architect allows the Linux file system to be customized and minimized for embedded applications using flash memories as small as 2 GB.

Architect creates and processes a configuration file based upon your selections and performs actual RPM package installation. It prompts you to insert the necessary RedHawk, Red Hat, and NightStar media depending upon the features selected.

Creating a root File System for Embedded Target Boards

To create a root file system that can be used on a single board computer, use RedHawk Architect on a RedHawk or Red Hat host system to perform the following steps:

1. Create an image by selecting the software to be installed and building the image.
2. Configure the image.
3. Customize the image for your embedded application.

4. Flash the image to install it on your target boards.

These procedures are described in the sections that follow. The steps may be repeated to change the image and/or flash it any number of times.

Running Architect

For instructions for installing RedHawk Architect, refer to the *RedHawk Architect Release Notes*.

Architect must be run as the root user.

To run Architect, type **architect** at a shell prompt:

```
# architect
```

When Architect starts, a dialog appears presenting you with the option to start a new session or load an existing session.



Figure 1-1 Opening RedHawk Architect Dialog

To start a new session, click on the **New** button. See “Creating a New Session” on page 1-3 for details.

A session can be saved at any time and loaded later to continue work on the file system image. To edit an existing session, click on the **Open** button. See “Editing an Existing Session” on page 1-39 for details.

When the **Close** button is clicked, the RedHawk Architect main window appears, as shown in Figure 1-2.






Figure 1-2 RedHawk Architect Main Window

Your choices are:

- start a new session by clicking on the New Session icon  or selecting **New Session** from the **File** menu along the top of the window. See “Creating a New Session” on page 1-3 for details.
- edit an existing session by clicking on the Open Session icon  or selecting **Open Session** in the **File** menu. See “Editing an Existing Session” on page 1-39 for details.

Creating a New Session

An Architect session describes all decisions made about a particular file system image, including:

- the target SBC
- which software should be installed
- how the software should be configured


When you select the **New** button from the opening Architect dialog, or the **New Session** icon  or **New Session** from the **File** menu along the top of the RedHawk Architect main window, the **New Session** dialog, shown below, displays.



Figure 1-3 New Session Dialog

This dialog enables you to define the target board and its various characteristics using the fields described below.

Target Board

Specify the target board from the dropdown. Select **None** to build a generic image that does not target any particular board. You may indicate specific hardware parameters such as root device by using the **Configure Image** toolbox.

Root Device

Select the root device to use on the target board from the dropdown. The choices available depend on the board you have selected.

Root Device Size

Select the size of the selected root device that is installed on your board from the dropdown. The choices available depend on the board you have selected.

I/O Expansion

This section shows I/O expansion connectors that are available on the board you have selected. For each I/O expansion connector, you may designate an expansion module that you may have connected to it. The choices available depend on the board you have selected.

OK

Click on this button when all desired selections have been made. This dialog closes and the RedHawk Architect main window is activated.

Cancel

Click on this button to cancel any changes made. The dialog closes and you are returned to the RedHawk Architect main window.

Selecting Software to Install in the Image

To select the software to install in the file system image, click on **Select Products** from the toolbox on the left side of the RedHawk Architect main window. This allows you to select software from the following three groups:

- Red Hat Enterprise Linux packages
- RedHawk Linux operating system
- NightStar RT tools

Some initial selections are made for you by default; e.g. the core RedHawk OS.

The **Estimated Image Size** gauge at the top of the RedHawk Architect main window indicates the approximate size the file system image will be when built. It also indicates the percentage of the target board's root device that will be consumed by the image.

Once an image is built, you may click on the **Estimated Image Size** label to calculate the actual image size as it is stored on disk. The **Estimated Image Size** gauge will be updated to reflect the *current* actual size.

The spin control box to the right of the **Estimated Image Size** gauge may be used to change the desired maximum size of the image. This value cannot exceed the known size of the root device but it can be made smaller. If the size of the root device is unknown the maximum value allowed is 1 terabyte.

Selecting Red Hat Packages

To select Red Hat Enterprise Linux packages for the file system image, click on the **Red Hat Packages** selection from the **Select Products** toolbox.

Red Hat packages may be navigated by way of several "Package Views". Select the desired package view from the **Package Views** dropdown. The following views are available and are described in the subsections that follow.

- Embedded RedHawk Package Groups
- Red Hat Package Groups
- All Packages
- Selected Packages

Using the Embedded RedHawk Package Groups View

The Embedded RedHawk Package Groups view provides a view of some Red Hat packages organized into groups. The groups of packages have been optimized for embedded RedHawk systems and are meant to simplify the task of choosing packages for common functionality. This view is shown in Figure 1-4.

Packages may be selected or deselected by choosing a package group in the upper pane and then checking or un-checking packages in that group in the lower pane. All packages may be selected with the **Select all packages in group** button.

The **Undo** button cancels out your last select or unselect operation.




Figure 1-4 Selecting Red Hat Packages, Embedded RedHawk Package Groups View

Using the Red Hat Package Groups View

The Red Hat Package Groups view provides a view of Red Hat packages organized in a hierarchy of groups. The package group hierarchy is the standard Red Hat package group hierarchy. This view is shown in Figure 1-5.

Packages may be selected or deselected by choosing a package group in the upper pane and then checking or un-checking packages in that group in the lower pane. All packages may be selected with the **Select all packages in group** button.

The **Undo** button cancels out your last select or unselect operation.




Figure 1-5 Selecting Red Hat Packages, Red Hat Package Groups View

Using the All Packages View

The All Packages view, as shown in Figure 1-6, provides a linear list of all Red Hat packages.




Figure 1-6 Selecting Red Hat Packages, All Packages View

Packages may be selected or deselected from this list. The Show only packages matching box allows you to search for packages by name.

All packages can be selected by clicking on the Select all packages button.

The Undo button cancels out your last select or unselect operation.

Using the Selected Packages View

The Selected Packages view, as shown in Figure 1-7, provides a linear list of all Red Hat packages that are currently selected for installation.




Figure 1-7 Selecting Red Hat Packages, Selected Packages View

Packages may be deselected from this list. The Show only packages matching box allows you to search for packages by name.

To include the required packages in the list, check the Show required packages checkbox. When this box is unchecked, only the optional packages are shown.

The Undo button cancels out your last select or unselect operation.

Selecting RedHawk OS Options

To select RedHawk Linux OS and kernels for the file system image, click on the RedHawk selection from the Select Products toolbox. The RedHawk page, shown in Figure 1-8, displays.




Figure 1-8 Selecting RedHawk Options

The Core OS product is required and cannot be deselected. Other RedHawk products will be available in future releases.

Select which RedHawk kernel(s) to install by checking the appropriate checkbox(es): Standard, Trace and/or Debug.

Selecting NightStar RT Options

To select NightStar RT tools for the image, click on the NightStar selection from the Select Products toolbox. The NightStar page, shown in Figure 1-9, displays.




Figure 1-9 Selecting NightStar Tools

Each NightStar tool is described in the righthand side of the page.

Click on the **Servers Only** radio button to indicate that only NightStar servers are to be installed in the image. You may select individual servers from the list by clicking on the checkboxes for each tool.

Click on the **Full Tool Set** radio button to indicate that NightStar servers and clients are to be installed in the image.

Configuring an Image (before building)

It is now possible to pre-configure a file-system image before the image has been built by selecting the first **Configure Image** from the toolbox on the left side of the RedHawk Architect main window. This section is only enabled before the build, and is identical to the steps described in configuring the image after the build, with the exception that there are no **Apply** buttons on these pages. See "Configuring an Image" on page 1-17 for more information.

Building an Image

To build the file system image by installing the selected software, select **Build Image** from the toolbox on the left side of the RedHawk Architect main window. The **Build Image** page shown in Figure 1-10 displays.




Figure 1-10 Build Image Page

Choose a directory in which to build the file system image and enter it in the **Target Directory** field, or click on the **Browse...** button to display a file browser from which to choose.

NOTE

Do not use `/tmp` as the image file directory. Packages like “tmp-watch” might remove files that have not been accessed in a certain number of days, thereby sabotaging the image directory.

Choose a name for the file system image and enter it in the Image Name field.

NOTE

Make sure that the directory you specify has enough free disk space to hold one or more file system images, each of which can be several gigabytes in size.

Click on the **Build** button to begin the build process. The rest of this section assumes that you have not previously ripped the ISOs from their respective media by clicking on the **Rip ISOs from media** button. Advanced users may wish to do that to avoid inserting DVD or CD media repeatedly, however that process is not covered in this document.

Dialogs are presented to guide you through the process of installing the software into the image. For example, you will be prompted to insert various DVD or CD media, as shown in Figure 1-11. Follow the directions to load the media, then click **OK** to begin.



Figure 1-11 Build Prompt to Insert RHEL Media

When **OK** is selected, the RHEL installation begins. The **Build Image** screen overlays the RedHawk Architect main window and tracks the progress, as shown in Figure 1-12.

Clicking **Abort** at any time in the build process aborts the build. A confirmation message then displays and you must click on the **Close** button to close the message box and reactivate the RedHawk Architect main window.




Figure 1-12 Status of RHEL Installation

A progress bar at the top of the **Build Image** screen shows the progress of the RHEL installation from the media.

A status area in the lower half of the screen tracks the progress of the complete build process. The status area can be changed to show an error log using the **View** dropdown.

View

When **Status** is selected, the overall progress messages are displayed. When **Error Log** is selected, the error log is displayed, which shows any error messages generated by the build process. Regardless of the **View** setting, critical error messages result in pop-up error dialogs with which you can interact.

Abort

Click on this button to abort the build. A confirmation dialog displays allowing you to confirm or decline aborting the build process.

OK

Once the build is completed or aborted, click on the **OK** button to close the **Build Image** screen and reactivate the RedHawk Architect main window.

When the RHEL installation is complete, the dialog shown in Figure 1-13 appears.



Figure 1-13 Build Prompt to Insert RedHawk Media

Load the RedHawk Linux media, then click OK. The RedHawk installation begins and the Build Image screen tracks the progress, as shown in Figure 1-14.




Figure 1-14 Status of RedHawk Installation

When the RedHawk installation is complete, the dialog shown in Figure 1-15 appears.




Figure 1-15 Build Prompt to Insert NightStar Media

Load the NightStar media, then click OK to begin. The NightStar installation begins and the Build Image screen tracks the progress, as shown in Figure 1-16.




Figure 1-16 Status of NightStar Installation

When all software is installed, the completion message shown in Figure 1-17 appears.




Figure 1-17 Build Completed Successfully Message

Click OK in the Build Status dialog, then click OK on the Build Image screen to close it and reactivate the RedHawk Architect main window.

Configuring an Image

To configure the file system image, select **Configure Image** from the toolbox on the left side of the RedHawk Architect main window. This allows you to configure the following four groups:

- General Settings
- Console
- Networking
- File System

Some initial selections are made for you by default.

Configuring General Settings

To configure time zone, root password and default system run level for the file system image, click on **General Settings** from the **Configure Image** toolbox. The **General Settings** configuration page appears, as shown in Figure 1-18.




Figure 1-18 General Settings Configuration Page

In the **Time Zone** section, select the proper time zone for your location from the dropdown. Click in the checkbox to indicate if your system clock uses UTC.

In the **Root Password** section, enter the root password in the **Password** field. Reenter it in the **Confirm Password** field.

In the **Run Level** section, select the desired default run level from the dropdown.

When all entries are complete, click on the **Apply general settings...** button to apply the settings to the image.

Configuring a Console

To configure a serial console for the file system image, click on **Console** from the **Configure Image** toolbox. The **Console Configuration** page appears, as shown in Figure 1-19.




Figure 1-19 Console Configuration Page

Click on the **Configure a serial console** checkbox to activate the fields that define the port and baud rate for the console.

Select a port from the **Serial Port** dropdown.

Select a baud rate from the **Baud Rate** dropdown.

When all selections have been made, click on the **Apply console settings...** button to apply the settings to the image.

Configuring Networking

To configure networking for the file system image, click on **Networking** from the **Configure Image** toolbox. The **Network Configuration** page appears, as shown in Figure 1-20.




Figure 1-20 Network Configuration Page

All available network devices are listed in the Network Devices section.

To configure a particular network device, click on the device to select it, then click on the Edit Device Configuration button. The Configure Network Device dialog shown in Figure 1-21 displays.




Figure 1-21 Configure Network Device Dialog

The selected network device is displayed at the top of the dialog.

Click on the Enabled On Boot checkbox to enable/disable the device automatically on boot.

Select Dynamic or Manual IP address configuration by clicking on the appropriate radio button. For manual configurations, enter the IP address and netmask in the appropriate fields.

Click on OK to apply the settings to the image and close the dialog. Click Cancel to cancel changes.

On the Network Configuration dialog (Figure 1-20) under the Manual Settings (not using DHCP) checkbox, supply the hostname, default gateway, domains, primary and secondary DNS server addresses in the appropriate fields. Uncheck the checkbox if a DHCP server will be providing these parameters instead.

When all selections have been made, click on the Apply network settings... button to apply the settings to the image.

Configuring File System Options

To configure file system options for the file system image, click on File System from the Configure Image toolbox. The File System Configuration page appears, as shown in Figure 1-22.




Figure 1-22 File System Configuration Page

Indicate the desired root device in the Root Device field.

Select the size of the root device from the Root Device Size dropdown.

Check the Mount with “noatime” option box to mount the root file system with the *noatime* option. This helps to minimize the number of writes to the root device when root is not mounted read-only.

Check the Mount read-only box to mount the root file system *read-only*. If the root device is a flash device, this will help preserve the life of the device.

Check the Mount resources listed in `/etc/rwtab` in `tmpfs` box to mount the files and directories listed in `/etc/rwtab` as writable but temporary files in a `tmpfs` file system. This is required to make a read-only root file system work. If root is not mounted read-only, this option is still useful to help minimize the number of writes to the root device.

Customizing an Image

To further customize the file system image, select **Customize Image** from the toolbox on the left side of the RedHawk Architect main window. This allows you to customize the following five groups:

- Kernel Manager
- Additional RPMs
- File Manager
- Chroot Shell
- Image Cleanup

Each of these customizations will be fully described in the following sections.

Kernel Manager

To customize kernel settings for the file system image, click on **Kernel Manager** from the **Customize Image** toolbox. The **Kernel Manager** page appears, as shown in Figure 1-23




Figure 1-23 Kernel Manager Page

The **Kernel Manager** allows you to perform different functions with the kernel configuration in the target image.

The **Kernel to Boot** area allows you to choose which installed kernel should be the default kernel that boots in the target image. Any change made to this setting is customized in the target image immediately.

The **Custom Kernel Operations** area contains several different functions related to configuring and building custom kernels for the target image. These functions will be described in the following sections.

Note that only one custom kernel configuration, and therefore one custom kernel, can be associated with a specific target image at any given time.

Configure Custom Kernel

The **Configure Custom Kernel** button begins the process of creating a custom kernel configuration. The custom kernel configuration is based upon the kernel configuration that is selected in the dropdown menu that is immediately to the right of the **Configure Custom Kernel** button.

The choices in the dropdown are: **Static**, **Trace-Static**, **Debug-Static** and **Custom**. The first three create new configurations based on the configurations of the standard RedHawk kernels. The **Custom** choice bases the new configuration on the current custom kernel configuration that is associated with the image; thus, the **Custom** choice can be used to further customize a configuration that you have already customized or imported.

Pressing the **Configure Custom Kernel** button will bring up two different dialog windows. The first dialog window displays overall configuration progress status, as shown in Figure 1-24.




Figure 1-24 Custom Kernel Dialog

This window shows the status of running the **ccur-config** command in the target image kernel source directory. The **ccur-config** command will eventually bring up the Linux Kernel Configuration window to customize the kernel, as shown in Figure 1-25.




Figure 1-25 Linux Kernel Configuration Dialog

This window allows you to customize almost any aspect of the custom kernel configuration. It is expected that users who are performing this step have a thorough understanding of Linux kernel configuration.

Note that you must **Save** the kernel configuration before you exit the Linux Kernel Configuration window. Failure to **Save** the configuration will result in an error being displayed in the Custom Kernel Manager dialog window and no changes to the custom kernel configuration will be made.

NOTE

You may not see the Linux Kernel Configuration Dialog appear but instead see the following error message displayed in the Custom Kernel Dialog while running `ccur-config`:

```
Starting graphical configuration tool...
make[1]: *** No rule to make target
'scripts/kconfig/.tmp_qtcheck'
make: *** [xconfig] Error 2
```

If this occurs it means that the `qt-devel` and possibly `qt` RPMs are not installed on the host system. Ensure that these RPMs are installed on the host system and the errors should disappear.

Import Kernel Configuration

The Import Kernel Configuration button allows you to choose a configuration file on the host system and import it to become the custom kernel configuration in the target image.

Note that once a custom kernel configuration has been imported you can further customize it by using the Configure Custom Kernel button and selecting the Custom kernel to base the configuration on.

Export Kernel Configuration

The Export Kernel Configuration button allows you to copy the target image's current custom kernel configuration to the host system.

Build Custom Kernel

The Build Custom Kernel button allows you to build a complete and installed custom kernel in the target image. You must first have created a custom kernel configuration, either by using the Configure Custom Kernel button or by using the Import Kernel Configuration button.

Building a custom kernel compiles each file that comprises the Linux kernel and this process can take quite a bit of time to complete. Once you start the process, you will see the Custom Kernel Manager dialog appear, as shown in Figure 1-26 and it will describe the entire process.




Figure 1-26 Initial Build Progress

Initially **ccur-config** will be invoked and once that completes the kernel build stages will begin, as shown in Figure 1-27.




Figure 1-27 Kernel Build Stages

Finally, once the entire build and install process is complete, the kernel source tree will be cleaned to free up the temporary space used to build the kernel. At this point the entire build process will be complete, as shown in Figure 1-28.




Figure 1-28 Kernel Build Complete

The custom kernel automatically becomes the default kernel to boot. If this choice is not desired, change the kernel to boot using the **Kernel To Boot** area as described above.

Remove Custom Kernel

The **Remove Custom Kernel** button allows you to remove the current custom kernel from the target image. This will remove the entry in **grub.conf** as well as all of the associated kernel files in the image.

Note that the custom kernel configuration itself is not removed. Thus, it is still possible to build a custom kernel based on the current custom kernel configuration that still remains in the target image.

Additional RPMs

To install additional RPMs into the target file system image manually, click on **Additional RPMs** from the **Customize Image** toolbox. The **Install Additional RPMs** page appears, as shown in Figure 1-29.




Figure 1-29 Install Additional RPMs Page

The Install Additional RPMs page can be used to locate RPM files on the host system and then easily install them into the target file system image. Note that the interface supports multiple selection; if you have a set of RPMs that have dependencies upon each other you will need to select all of the RPMs simultaneously to have them properly installed together into the target file system image.

Installing Board Support Packages

Concurrent provides *Board Support Packages* (BSPs) for several supported SBCs. These BSPs are distributed as RPMs that may be installed in an image using the Additional RPMs page as described above. Contact Concurrent (support@ccur.com or 1-800-245-6453) for information on how to obtain BSPs for a particular SBC.

File Manager

To copy various files into the target file system image manually, click on File Manager from the Customize Image toolbox. The File Manager page appears, as shown in Figure 1-30.




Figure 1-30 File Manager Page

The File Manager page supports many features including multiple selection, the ability to create new directories in the target file system image, and the ability to delete files in the target system image.

Chroot Shell

To customize the target file system image manually, click on the Chroot Shell from the Customize Image toolbox. The Chroot Shell page appears, as shown in Figure 1-31




Figure 1-31 Chroot Shell Page

From this toolbox you can open a “chroot” shell in a terminal window. Select the type of terminal from the dropdown and click on the RUN chroot shell button. A terminal screen opens, as shown in Figure 1-32




Figure 1-32 chroot Shell

This provides a shell with the root directory being the file system image directory. All changes made to system files (including software installed or removed) will be done in the file system image directory only. The host's root file system will not be affected.

Exit the shell when changes are complete.

Image Cleanup

You may reduce the size of the file system image by removing various types of files that may be unnecessary for the image. To remove unnecessary files from the image, click on **Image Cleanup** in the **Customize Image** toolbox. The **Image Cleanup** page appears, as shown in Figure 1-33.




Figure 1-33 Image Cleanup Page

Select the types of files to remove from the file system image and click the Remove selected from image button.

To remove the RPM database from the file system click the Remove RPM database button. Once this is done you will lose all ability to manage RPMs in the image. This cannot be undone. Only do this once you are sure you do not have to add or update any more RPMs in the image.

Flashing an Image

To copy a target root file system image to a CompactFlash device, select **Flash Image** from the toolbox on the left side of the RedHawk Architect main window. This will display the **Flash Image** page, as shown in Figure 1-34.




Figure 1-34 Flash Image Page

The **Flash...** button allows you to copy a root file system image onto a CompactFlash that is connected directly to the host machine via a USB-to-CompactFlash adapter. Note that IDE/SATA CompactFlash adapters are not supported at this time.

CompactFlash devices can be bought inexpensively at many retail stores that sell computer accessories. Note that the duration of the flashing process depends upon the performance rating of the specific CompactFlash device. It is recommended to use CompactFlash devices that have a minimum of a 40MB/s read/write performance rating.

Pressing the **Flash...** button will begin copying the target root file system onto the CompactFlash device by bringing up the **Flash Image** dialog, as shown in Figure 1-35.




Figure 1-35 Flash Image Dialog

The host system will now be scanned for attached CompactFlash devices and a choice will be presented to the user, as shown in Figure 1-36.




Figure 1-36 Flash Destination Choice

Press OK to choose the appropriate device, confirm the operation one last time and then the copy will begin, as shown in Figure 1-37.




Figure 1-37 Flash Copy Begins

Note that no initial check is made to determine whether the image will fit onto the size of the selected CompactFlash device. If the copy fails because of insufficient space, an error message will be displayed, as shown in Figure 1-38.




Figure 1-38 Flash Dialog Error

If the CompactFlash is large enough to hold the image, and no other error occurs during the copy, a success dialog will be presented, as shown in Figure 1-39.




Figure 1-39 Flash Copy Completed

Once the copy has completed successfully the CompactFlash can then be placed onto the intended target board and the board can be reset to boot into a fresh RedHawk installation.

Using Cluster Manager to Deploy an Architect Image

RedHawk Linux Cluster Manager provides Architect users with additional methods of deploying file system images. With Cluster Manager, images may be remotely installed directly to disk devices on target systems, or target systems may be booted diskless from an Architect image.

Using Cluster Manager to install Architect images is useful when the root device on the target system is not a CompactFlash that can be easily removed. The root device may be any kind of hard disk or solid state device using various interfaces such as IDE, SCSI or SATA.

Using Cluster Manager to diskless-boot Architect images is especially useful during development of an embedded application and the file system image. Test systems may be quickly booted to test each iteration of the file system image. When diskless booting an Architect image, the image remains in-place where it was built and configured by Architect. Various services are configured by Cluster Manager to allow target systems to diskless-boot the image. Multiple target systems may diskless-boot the same image simultaneously.

To begin using Cluster Manager with Architect images, install Cluster Manager as described in the *RedHawk Linux Cluster Manager User's Guide*, then run the **cm-import** command to import an Architect image into Cluster Manager.

Consult the *RedHawk Linux Cluster Manager User's Guide* for details on installing or diskless-booting images.


Editing an Existing Session

A session can be saved at any time and loaded later to continue work on a file system image.

To save the current session click on the Save Session icon  or on **Save Session** in the File menu. Selecting the Save As icon  or **Save Session As** in the File menu displays a file selection dialog.

NOTE

Performing a **Save Session As** will not save any associated image path with the session file. This is useful for cloning sessions to be used to create multiple images. Always use **Save Session** if you want the image path to be saved in the session file.

To load an existing session, click on the Open Session icon  or on **Open Session** in the File menu. You may also click on the **Open** button from the opening dialog when Architect first starts.

Updating Software with NUU

Concurrent's Network Update Utility (NUU) is a graphical user interface which allows you to install, update and remove RPM packages on a system. The packages are downloaded from a remote yum repository. For more information about NUU, see <http://redhawk.ccur.com/updates/index.html>.

NUU may be used to maintain the software installed in a file system image. NUU is an X-based application. Running X applications under a chroot shell requires the following special X configuration on the host system:

1. Run the **gdmsetup** command and uncheck the box that reads "Deny TCP connections to Xserver" under the "Security" tab.

```
# gdmsetup
```

2. Restart the X server:

```
# killall Xorg
```

3. Run the command:

```
# xhost +
```


Paths

/etc/rwtab 1-22

A

Architect

- introduction 1-1
- main window 1-3
- opening dialog 1-2
- running 1-2

B

- baud rate 1-19
- Board Support Packages 1-30
- building an image 1-12

C

- ccur-config 1-25, 1-28
- chroot shell 1-31
- Cluster Manager 1-38
- CompactFlash device 1-35
- configuring an image 1-11, 1-17
- console 1-18
- copy files into image 1-31
- create new directories in image 1-31
- creating a new session 1-2, 1-3
- Custom Kernel
 - build 1-27
 - configuration 1-24
 - remove 1-29
- customizing an image 1-23

D

- default gateway 1-21
- delete files in image 1-31
- diskless booting 1-38
- domains 1-21

E

- editing an existing session 1-2, 1-3, 1-39

F

- File Manager 1-31
- flash error 1-37
- flashing an image 1-35

H

- hostname 1-21

I

- Image Cleanup 1-33
- install additional RPMs 1-29
- installing software 1-5, 1-12

K

- Kernel
 - boot selection 1-24
 - configuring 1-24
- Kernel Configuration
 - export 1-27
 - import 1-27
- Kernel Manager 1-24

M

- main window 1-3

N

- networking 1-19
- new session 1-2, 1-3
- New Session dialog 1-4
- NightStar installation options 1-10

noatime file system option 1-22
NUU 1-39

P

primary DNS server 1-21

R

read-only root file system 1-22
Red Hat packages 1-5
RedHawk installation options 1-9
remote installation 1-38
Remove RPM database 1-34
Remove selected from image 1-34
root password 1-17
running Architect 1-2

S

saving a session 1-2, 1-3, 1-39
secondary DNS server 1-21
serial port 1-19
software to install 1-5
system run level 1-17

T

time zone 1-17
tmpfs file system 1-22

U

updating software with NUU 1-39

X

X configuration 1-39